


RU2 Two relay remote unit for secure installations

RU2 is a 2 relay remote control unit for the B100-SA/DINB100-SA biometric readers and the MTPX-MF-SA/DINMTPX-MF-SA MIFARE proximity readers. If secure installation is needed, the biometric reader can be connected to remote relay unit at secured area.






FEATURES


- Power supply:
- Output:

- Output maximum current: 3A, 250V AC, 24V DC
- Inputs:
- Output timing:
- Operating temperature:
- Housing:
- Mounting:
- PCB size:
- Housing size:

12V DC, 100mA Two relays NO/NC contacts 3A, 250V AC, 24V DC Two inputs for activating outputs Pulse 1-60 sec or toggle 0-50C, non condensing DIN RAIL size 2 box or PCB only DIN RAIL (for model with housing) 86 x 32 mm, 4 fixing holes dia. 3mm 36 x 90 x 32,2mm (DINrail box)

Compatible devices: Standalone biometry B100 series, DIN hotel system





DIMENSIONS

32,2mm **APPLICATION DIAGRAM** BUS R5485 (50m max.) Alarm Þ OR **B100-SA** MTPX-MF-SA Standalone Standalone **Biometric Reader** MIFARE Reader RU2 - Optional 2 Door remote Relay Unit secured area usecured area

All product specifications are subject to change without notice

